

# Making a Low cost, simple and robust 6kW, 50HZ Pure Sine Wave, 48vdc to 230vac, INVERTER.

## PCB Component details for the 6-15kW OzControl Board.

These Boards have been designed for easily obtainable components and parts. This list will be updated as required. Most of the component/parts details are from Ebay and may be purchased there, however some parts may only be found on Allibaba, so the Web Link is given.

### Please find below a list of the majority of parts required.

EG8010 LQFP-32 Sine wave inverter chip, HN1518HT1536, <http://www.aliexpress.com/item/10pcs-lot-New-EG8010-LQFP-32-Sine-wave-inverter-chip/32605461001.html>.

Single sided copper clad PCB, 86mm x 170mm x 1.5mm 35um thick copper.

0.65mm to 0.8mm QFN32/QFP32 IC DIP Mounting PCB Adapter Converter Plate for SMD chip, (1 off). .... 40Pin (we need 2 off 16pin), 2.54mm Male & Female SIL Header Socket Row Strips PCB Connectors.

HC-49S 12.000MHZ 12MHZ 20PF DIP Crystal Oscillator, (1 off).

IR2110PBF IR2110 IR FETS DRIVER CHIP DIP-14 IC 5V, (2 off). .... TIP35C TRANSISTOR, (2 off) .... 5.6v (1.3W) Zener Diode, BZX55C5V6, (1 off). .... 13v (1.3W) Zener Diode, BZX85C5V6, (1 off). ... DIODES fast/RAPIDES FR107 - 1A, (2 off). .... IN4007 Diode - Rectifier - 1A 1000V , (8 off). ...

DC 2.5V-3.0V 5mm Red LED Lamp Emitting Diode, (1 off).

Monolithic Ceramic Chip Capacitor 475 4.7UF 50V 20% 5.08mm Pitch, (5 off). .... CBB61 Polypropylene Film Motor Start Run Capacitor, 2uF 50/60Hz 450V AC, (2off). ... 22pF - Ceramic Disc Capacitor, 50V , (2 off). .... 100nf Ceramic Disc Capacitor, 50V, (9 off). .... 1nf Ceramic Disc Capacitor, 50V, (1 off). ... 10uF Electrolytic Capacitor, (can), 63V (max) 105°, (6 off). ... 100uF Electrolytic Capacitor, (can), 63V (max) 105°, (1 off).

100r Ohm 1/2W Metal Film Resistor, (2 off)...Resistor 2K Variable TRIMMER, (1 off). .... Resistor 10K Variable TRIMMER, (1 off). .... 120 Ohm 5W Ceramic Wirewound Resistor, (1 off). .... 0.6W Metal Film Resistor 10K , (4 off). ... 0.6W Metal Film Resistor 50K , (4 off). ... 0.6W Metal Film Resistor 1K , (3 off).

IDC Straight Latched PCB Plug (male) Connector 10 Way, (1 off). ... Molex KK Connector Housing 2 Way (3 off). ... Molex KK Straight Header Connector 2 Way (3 off) & 6 Molex crimp terminals to match. ....

14-Pin DIL DIP IC Socket PCB Mount Connector, (2 off). ....

-50~70°C LCD Panel Digital Thermometer Temperature Meter Probe sensor, (1 off). ...

PCB Blade 6.3mm Connector Terminal Vertical (2 off).

DL-CT08CL5 20A/10MA 2000/1 0~120A MICRO CURRENT TRANSFORMER X9N0, (1 off), for the 230vac sense.